




SIMPLICITY.
APPLIED.

MN01-LTE-M-PX

Cellular Communicator
Quick Installation Manual

Wiring the Communicator to the Paradox Alarm Panel via Keybus*

- Red (+): ↔ 12-15V DC Power Supply
Black (-): ↔ Ground
Yellow (Y): ↔ YEL
Green (G): ↔ GRN



* Panel compatibility list for Keybus integration is available at support.m2mservices.com

- ✓ **WARNING:** The wiring should be done only when the panel and the communicator are disconnected from the powerline!
- ✓ Connect the antenna and place it outside of the alarm panel's box.
- ✓ Connect + and - of the communicator to a max of 12V - 15V DC power supply.
- ✓ **WARNING: THE USB PORT TO BE USED WITH M2M ADD-ON MODULES ONLY.**

LED Indicator

- ✓ Slow flashing – trying to establish connection
- ✓ Constantly On – connection established at good signal level
- ✓ Constantly On, blinking every 5 sec. – connection established at low signal level
- ✓ Fast flashing – transferring data.



SIMPLICITY.
APPLIED.

MN01-LTE-M-PX

Cellular Communicator

Quick Installation Manual

RControl App (end user) Credentials



Download the RControl mobile application on your Android or iOS device by scanning the QR codes.

Remote Arming/Disarming via Keybus for Paradox Alarm Panels

Panel compatibility list for Keybus integration is available at support.m2mservices.com

- ✓ Wire the device to the panel according to the Keybus wiring diagram.
- ✓ To perform **Sync with Panel**, log in to the RControl App, go to **Settings** > **Remote Arming/Disarming**, press **Sync with Panel**, and follow the instructions in the app:

- Via the **Enter Installer Code** option: By entering the installer code in the RControl mobile app, **or**
- Via the **Use Keypad*** option: By entering the installer code on the panel keypad.

* Depending on the keypad model, there are two options for entering the installer code:

- For MG/SP alarm panels used with K32LCD+, K32+, PA6, K35, K636, K10V, K10H keypads: Press the Power button  of the keypad followed by the installer code.
- For MG/SP alarm panels used with TM70, TM50 keypads, you can perform Sync with Panel: From the main menu of the keypad, click the **Menu** button > **System Setup**, and enter the installer code.

- ✓ Perform **Sync with Panel** every time the panel programming has been changed.

ⓘ Unless prompted in the app, **DO NOT** operate the keypad during the sync process.